

Frequency converter
EFC 3610



Frequency converter

EFC 3610

Documentation



- Power range 1 x AC 230 V 0.4 kW to 3 x AC 400 V 22.0 kW
- Use in HD (heavy duty) or ND (normal duty) mode
- Integrated brake chopper and mains filter
- Integrated operating panel for simple, fast commissioning
- Expandability through I/O and fieldbus modules

EFC3610 is a universal, low-cost frequency converter for reliable speed control and demand-oriented energy supply. V/f control, easy installation and commissioning as well as an increased power range enable a wide range of applications.

Technical data

	EFC3610-0K40-1P2	EFC3610-0K75-1P2	EFC3610-1K50-1P2	EFC3610-2K20-1P2	EFC3610-0K40-3P4	EFC3610-0K75-3P4	EFC3610-1K50-3P4	EFC3610-2K20-3P4	
Performance data									
Rated output HD operation	[kW]	0.4	0.75	1.5	2.2	0.4	0.75	1.5	2.2
Continuous rated current HD operation	[A]	2.4	4.1	7.3	10.1	1.3	2.3	4	5.6
Motor rated voltage	Three phase, 0 V ... mains voltage								
Output frequency	0 ... 400 Hz								
Mains voltage	1 AC	1 AC 200 ... 240 V (-10 % / +10 %)							
	3 AC					3 AC 380 ... 480 V (-15 % / +10 %)			
Frequency	50 ... 60 Hz (±5 %)								
Overload capacity HD operation	150 % for 60 s, 200 % for 1 s								
Brake chopper / resistor									
Braking resistance	External								
Brake chopper	Internal up to 22 kW								
Ambient conditions									
Permissible temperature (operation)	-10 ... +45 °C (Derating 1.5 % of the output power per 1 °C from 45 ... 55 °C)								
Permissible relative humidity (operation)	< 90 % (no condensation)								
Max. installation height	1000 m (> 1000 m Derating 1 % of the output power pro 100 m)								
Protection category	IP 20								
Functions									
Control technology	V/f								

Frequency converter

EFC 3610

Pulse width modulation (PWM), adjustable in 1 kHz steps	[kHz]	1 ... 15				
Speed control range	Without pulse generator	1 : 50				
Start-up torque	V/f	100% at 1.5 Hz; 150% at 3 Hz				
Frequency resolution	Digital	0.01 Hz				
	Analog	1/1000 of the output frequency				
V/f curve		linear, quadratic, freely definable				
Ramps		linear, S-curve				
DC disc brake	Start frequency	0 ... 50 Hz				
	Braking time	0 ... 10 s				
Automatic PWM frequency adjustment		Load-dependent PWM frequency adjustment				
Integrated control		Integrated sequential circuit				
Frequency setting tolerance	Analog	0.4 %				
	Digital	0.04 %				
Controller		PID				
Bus systems		Modbus RTU (with Multi-Ethernet Modbus TCP)				
		PROFIBUS, CANopen, Multi-Ethernet (ext. options)				
Status messages via digital outputs		Operation, target value achieved, etc.				
Number of digital inputs 24 VDC		5 (of which 1x pulse train 50 kHz)				
Number of digital outputs 24 VDC / 50 mA		1 (pulse train 32 kHz)				
Number of relay outputs 230 VAC / 30 VDC / 3 A		1				
Number of analog inputs 0 ... 10 V or 0 ... 20 mA		2				
Number of analog outputs 0 ... 10 V or 0 ... 20 mA		1				
Display		Dust cover with 4 diagnostic LED				
		LED 5 digit (optional)				
		LCD (optional)				
Status LED		Rotation direction and operating status				
Weight						
Weight	[kg]	1.5	1.9	2.6	1.5	1.9
Norms and Standards						
Certification		CE UL cUL EAC C-Tick (RCM)				

	EFC3610-3K00-3P4	EFC3610-4K00-3P4	EFC3610-5K50-3P4	EFC3610-7K50-3P4	EFC3610-11K0-3P4	EFC3610-15K0-3P4	EFC3610-18K5-3P4	EFC3610-22K0-3P4
Performance data								

Frequency converter

EFC 3610

Rated output HD operation	[kW]	3	4	5.5	7.5	11	15	18.5	22
Rated output ND operation	[kW]	0		7.5	11	15	18.5	22	30
Continuous rated current HD operation	[A]	7.4	9.7	12.7	16.8	24.3	32.4	39.2	45
Continuous rated current ND operation	[A]	0		16.8	24.3	32.4	39.2	45	60.8
Motor rated voltage	Three phase, 0 V ... mains voltage								
Output frequency	0 ... 400 Hz								
Mains voltage	3 AC	3 AC 380 ... 480 V (-15 % / +10 %)							
Frequency	50 ... 60 Hz (± 5 %)								
Overload capacity HD operation	150 % for 60 s, 200 % for 1 s								
Brake chopper / resistor									
Braking resistance	External								
Brake chopper	Internal up to 22 kW								
Ambient conditions									
Permissible temperature (operation)	-10 ... +45 °C (Derating 1.5 % of the output power per 1 °C from 45 ... 55 °C)								
Permissible relative humidity (operation)	< 90 % (no condensation)								
Max. installation height	1000 m (> 1000 m Derating 1 % of the output power pro 100 m)								
Protection category	IP 20								
Functions									
Control technology	V/f								
Pulse width modulation (PWM), adjustable in 1 kHz steps	[kHz]	1 ... 15							
Speed control range	Without pulse generator	1 : 50							
Start-up torque	V/f	100% at 1.5 Hz; 150% at 3 Hz							
Frequency resolution	Digital	0.01 Hz							
	Analog	1/1000 of the output frequency							
V/f curve	linear, quadratic, freely definable								
Ramps	linear, S-curve								
DC disc brake	Start frequency	0 ... 50 Hz							
	Braking time	0 ... 10 s							
Automatic PWM frequency adjustment	Load-dependent PWM frequency adjustment								
Integrated control	Integrated sequential circuit								
Frequency setting tolerance	Analog	0.4 %							
	Digital	0.04 %							
Controller	PID								
Bus systems	Modbus RTU (with Multi-Ethernet Modbus TCP)								
	PROFIBUS, CANopen, Multi-Ethernet (ext. options)								

Frequency converter

EFC 3610

Status messages via digital outputs	Operation, target value achieved, etc.							
Number of digital inputs 24 VDC	5 (of which 1x pulse train 50 kHz)							
Number of digital outputs 24 VDC / 50 mA	1 (pulse train 32 kHz)							
Number of relay outputs 230 VAC / 30 VDC / 3 A	1							
Number of analog inputs 0 ... 10 V or 0 ... 20 mA	2							
Number of analog outputs 0 ... 10 V or 0 ... 20 mA	1							
Display	Dust cover with 4 diagnostic LED							
	LED 5 digit (optional)							
	LCD (optional)							
Status LED	Rotation direction and operating status							
Weight								
Weight	[kg]	2.6	3.9	4.3	5.7	6.4	8	8.5
Norms and Standards								
Certification	CE UL cUL EAC C-Tick (RCM)							

Dimensions**Dimensions**

Type	A [mm]	B [mm]	C [mm]	D [mm]	F [mm]	G [mm]	ØH [mm]
EFC3610-0K40-1P2	95	66	166	156	167	159	4.5
EFC3610-0K75-1P2			206	196	170	162	
EFC3610-1K50-1P2			231	221	175	167	
EFC3610-2K20-1P2	120	80	231	221	175	167	
EFC3610-0K40-3P4	95	66	166	156	167	159	
EFC3610-0K75-3P4			206	196	170	162	
EFC3610-1K50-3P4			231	221	175	167	
EFC3610-3K00-3P4	120	80	231	221	175	167	6.5
EFC3610-4K00-3P4							
EFC3610-5K50-3P4	130	106	243	228	233	225	
EFC3610-7K50-3P4							
EFC3610-11K0-3P4	150	125	283	265	241	233	
EFC3610-15K0-3P4							
EFC3610-18K5-3P4	165	140	313	295	241	233	
EFC3610-22K0-3P4							

Frequency converter

EFC 3610

Order details

Type code	Description	Material number:
EFC3610-0K40-1P2-MDA-7P-NNNNN-NNNN	0.4 kW, 1 AC 200 ... 240 V, 50/60 Hz, 2.4 A, LED Display	R912005713
EFC3610-0K40-1P2-MDA-NN-NNNNN-NNNN	0.4 kW, 1 AC 200 ... 240 V, 50/60 Hz, 2.4 A, Dust cover	R912005698
EFC3610-0K75-1P2-MDA-7P-NNNNN-NNNN	0.75 kW, 1 AC 200 ... 240 V, 50/60 Hz, 4.1 A, LED Display	R912005714
EFC3610-0K75-1P2-MDA-NN-NNNNN-NNNN	0.75 kW, 1 AC 200 ... 240 V, 50/60 Hz, 4.1 A, Dust cover	R912005699
EFC3610-1K50-1P2-MDA-7P-NNNNN-NNNN	1.5 kW, 1 AC 200 ... 240 V, 50/60 Hz, 7.3 A, LED Display	R912005715
EFC3610-1K50-1P2-MDA-NN-NNNNN-NNNN	1.5 kW, 1 AC 200 ... 240 V, 50/60 Hz, 7.3 A, Dust cover	R912005700
EFC3610-2K20-1P2-MDA-7P-NNNNN-NNNN	2.2 kW, 1 AC 200 ... 240 V, 50/60 Hz, 10.1 A, LED Display	R912005716
EFC3610-2K20-1P2-MDA-NN-NNNNN-NNNN	2.2 kW, 1 AC 200 ... 240 V, 50/60 Hz, 10.1 A, Dust cover	R912005701
EFC3610-0K40-3P4-MDA-7P-NNNNN-NNNN	0.4 kW, 3 AC 380 ... 480 V, 50/60 Hz, 1.3 A, LED Display	R912005717
EFC3610-0K40-3P4-MDA-NN-NNNNN-NNNN	0.4 kW, 3 AC 380 ... 480 V, 50/60 Hz, 1.3 A, Dust cover	R912005702
EFC3610-0K75-3P4-MDA-7P-NNNNN-NNNN	0.75 kW, 3 AC 380 ... 480 V, 50/60 Hz, 2.3 A, LED Display	R912005718
EFC3610-0K75-3P4-MDA-NN-NNNNN-NNNN	0.75 kW, 3 AC 380 ... 480 V, 50/60 Hz, 2.3 A, Dust cover	R912005703
EFC3610-1K50-3P4-MDA-7P-NNNNN-NNNN	1.5 kW, 3 AC 380 ... 480 V, 50/60 Hz, 4.0 A, LED Display	R912005719
EFC3610-1K50-3P4-MDA-NN-NNNNN-NNNN	1.5 kW, 3 AC 380 ... 480 V, 50/60 Hz, 4.0 A, Dust cover	R912005704
EFC3610-2K20-3P4-MDA-7P-NNNNN-NNNN	2.2 kW, 3 AC 380 ... 480 V, 50/60 Hz, 5.6 A, LED Display	R912005720
EFC3610-2K20-3P4-MDA-NN-NNNNN-NNNN	2.2 kW, 3 AC 380 ... 480 V, 50/60 Hz, 5.6 A, Dust cover	R912005705
EFC3610-3K00-3P4-MDA-7P-NNNNN-NNNN	3.0 kW, 3 AC 380 ... 480 V, 50/60 Hz, 7.4 A, LED Display	R912005721
EFC3610-3K00-3P4-MDA-NN-NNNNN-NNNN	3.0 kW, 3 AC 380 ... 480 V, 50/60 Hz, 7.4 A, Staubschutzkappe	R912005706
EFC3610-4K00-3P4-MDA-7P-NNNNN-NNNN	4.0 kW, 3 AC 380 ... 480 V, 50/60 Hz, 9.7 A, LED Display	R912005722
EFC3610-4K00-3P4-MDA-NN-NNNNN-NNNN	4.0 kW, 3 AC 380 ... 480 V, 50/60 Hz, 9.7 A, Dust cover	R912005707
EFC3610-5K50-3P4-MDA-7P-NNNNN-NNNN	5.5 kW, 3 AC 380 ... 480 V, 50/60 Hz, 12.7 A, LED Display	R912005091
EFC3610-5K50-3P4-MDA-NN-NNNNN-NNNN	5.5 kW, 3 AC 380 ... 480 V, 50/60 Hz, 12.7 A, Dust cover	R912005708
EFC3610-7K50-3P4-MDA-7P-NNNNN-NNNN	7.5 kW, 3 AC 380 ... 480 V, 50/60 Hz, 16.8 A, LED Display	R912005092
EFC3610-7K50-3P4-MDA-NN-NNNNN-NNNN	7.5 kW, 3 AC 380 ... 480 V, 50/60 Hz, 16.8 A, Dust cover	R912005709
EFC3610-11K0-3P4-MDA-7P-NNNNN-NNNN	11 kW, 3 AC 380 ... 480 V, 50/60 Hz, 24.3 A, LED Display	R912005093
EFC3610-11K0-3P4-MDA-NN-NNNNN-NNNN	11 kW, 3 AC 380 ... 480 V, 50/60 Hz, 24.3 A, Dust cover	R912005710
EFC3610-15K0-3P4-MDA-7P-NNNNN-NNNN	15 kW, 3 AC 380 ... 480 V, 50/60 Hz, 32.4 A, LED Display	R912005094

Frequency converter

EFC 3610

Type code	Description	Material number:
EFC3610-15K0-3P4-MDA-NN-NNNNN-NNNN	15 kW, 3 AC 380 ... 480 V, 50/60 Hz, 32.4 A, Dust cover	R912005711
EFC3610-18K5-3P4-MDA-7P-NNNNN-NNNN	18.5 kW, 3 AC 380 ... 480 V, 50/60 Hz, 39.2 A, LED Display	R912005723
EFC3610-18K5-3P4-MDA-NN-NNNNN-NNNN	18.5 kW, 3 AC 380 ... 480 V, 50/60 Hz, 39.2 A, Dust cover	R912005712
EFC3610-22K0-3P4-MDA-7P-NNNNN-NNNN	22.0 kW, 3 AC 380 ... 480 V, 50/60 Hz, 45.2 A, LED Display	R912006279
EFC3610-22K0-3P4-MDA-NN-NNNNN-NNNN	22.0 kW, 3 AC 380 ... 480 V, 50/60 Hz, 45.2 A, Dust cover	R912006278

SIDEX

Bosch Rexroth AG

Postfach 13 57
97803 Lohr, Germany
Bgm.-Dr.-Nebel-Str. 2
97816 Lohr, Germany
Tel. +49 9352 18-0
Fax +49 9352 18-8400
www.boschrexroth.com/electrics

Local contact information can be found at:

www.boschrexroth.com/adressen

SIDEX

The data specified above only serve to describe the product. As our products are constantly being further developed, no statements concerning a certain condition or suitability for a certain application can be derived from our information. The information given does not release the user from the obligation of own judgment and verification.

It must be remembered that our products are subject to a natural process of wear and aging.